

Set Output, Short-Term Version

The command sent must be composed of 6 or 12 characters:
or

RRRBBB
RRRBBBLLLLTTT

- <RRR> Relay activation time (tenths of seconds)
- <BBB> Buzzer activation time (tenths of seconds)
- <LLL> RGB colour. Each colour can be "0" or "1"
 - "000" OFF
 - "001" blue
 - "010" green
 - "011" cyan
 - "100" red
 - "101" violet
 - "110" yellow
 - "111" white
- <TTT> Time to Go to LED Lighting (tenths of seconds)

Set Output, Short-Term Version

In addition the command set can be composed also of 7 or 13 characters with the same values of the previous 6 and 12 with the addition of a "L" char at the beginning of the string:
Or

LRRRBBB
LRRRBBBLLLLTTT

- <L> = "L" means that the
- <RRR> Relay activation time
- <BBB> Buzzer activation time
- <LLL> Time to Go to LED Lighting
are expressed in seconds